

SYSTEMS AND METHODS FOR MULTI-TASKING, RESOURCE
SHARING, AND EXECUTION OF COMPUTER INSTRUCTIONS

Alexander Joffe

Dmitry Vyshetsky

5

CROSS REFERENCE TO RELATED APPLICATIONS

INSAI ¹ ~~Not applicable.~~

STATEMENT REGARDING FEDERALLY SPONSORED RESEARCH OR
10 DEVELOPMENT

Not applicable.

BACKGROUND OF THE INVENTION

The present invention relates to data processing,
15 and more particularly to pipelined instruction
execution, multi-tasking, and resource access
techniques.

Pipelining and multi-tasking increase processor
bandwidth. It is desirable to reduce the time and
20 complexity associated with these techniques.

In particular, when instruction execution is
pipelined, the processor may start executing an
instruction before it is known whether the instruction
should be executed. For example, suppose the processor
25 starts executing an instruction I1, and then starts
executing an instruction I2 before the I1 execution is
finished. If the I1 execution cannot be completed, the
instruction I2 should not be executed and has to be
purged from the pipeline. In fact, at any given time,
30 the processor may be executing more than one

instruction that have to be purged from the pipeline. It is desirable to reduce the circuit complexity associated with pipeline purging.

It is also desirable to reduce the overhead
5 associated with switching between different tasks in multi-tasking environments. To switch tasks, the operating system executed by the processor has to determine which task is to be executed next. The operating system also has to save register values used
10 by one task and load the registers with values used by another task. These functions can involve a fair number of operating system instructions. It is desirable to reduce the number of instructions associated with these operations.

15 It is also desirable to improve access to resources which maybe unavailable. An example of such a resource is a FIFO which may be empty when a processor is trying to read it, or which may be full when the processor is trying to write the FIFO. Before
20 accessing the FIFO, the processor polls a flag indicating whether the FIFO is available. It is desirable to improve the speed of accessing a resource which may be unavailable.

It is also desirable to provide simple
25 synchronization methods to synchronize use of computer resources by multiple tasks to avoid errors that could be caused by a task accessing a resource when the resource is set for access by a different task.

SUMMARY

The present invention provides in some embodiments efficient pipeline processors, multi-tasking processors, and resource access techniques.

5 In some instruction execution pipeline embodiments, the pipeline purge overhead is reduced or eliminated by limiting the number of instructions that the processor can execute in a row for any given task. Thus, in some embodiments, consecutive instructions are
10 executed by different tasks. Therefore, if an instruction cannot be executed, the next instruction still has to be executed because the next instruction belongs to a different task. Therefore, the next instruction is not purged from the pipeline.

15 In some embodiments, between any two instructions of the same task the processor executes a sufficient number of instructions from different tasks to eliminate any need for pipeline purging.

To reduce the overhead associated with task
20 switching, some embodiments include separate registers for each task so that the register values do not have to be saved or restored in task switching operations. In particular, in some embodiments, each task has a separate program counter (PC) register and separate
25 flags. In some embodiments, the task switching is performed by hardware in one clock cycle.

In some embodiments, a processor can access a resource without first checking whether the resource is available. If the resource is unavailable when the
30 processor executes an instruction accessing the

resource, the processor suspends the instruction, and the processor circuitry which was to execute the instruction becomes available to execute a different instruction, for example, an instruction of a different task.

Thus, in some embodiments, the processor keeps track of the state of all the resources (for example, FIFOs). (Unless specifically stated otherwise, the word "resource" as used herein means something that may or may not be available at any given time.) Signals are generated indicating the state of each resource, and in particular indicating which resource is available to which task. If a task attempts to access an unavailable resource, the task is suspended, and the processor can execute other tasks in the time slot that could otherwise be used by the suspended task. When the resource becomes available, the suspended task is resumed, and the instruction accessing the resource is re-executed.

To avoid synchronization errors when multiple tasks share one or more resources, in some embodiments after a task has finished accessing any one of the resources, the task does not get access to the same resource until after every other task sharing the resource has finished accessing the resource. Thus, in some network embodiments, different tasks share FIFO resources to process frames of data. Each task processes a separate frame of data. To process the frame, the task reads the frame address from a "request" FIFO. Then the task writes a command FIFO

with commands to a channel processor to process the frame. A second task performs similar operations for a different frame. The first task again performs the same operations for a still different frame. If
5 commands written for one frame get erroneously applied to another frame, the frames could be misprocessed.

To eliminate this possibility and to allow accurate matching between the frame addresses in the request FIFO and the commands in the command FIFO, the
10 following technique is used. First one task (say, T1) is allowed to access both the request FIFO and the command FIFO, but no other task is allowed to access these resources. Once the task T1 has finished accessing any resource, the resource is allowed to be
15 accessed by another task, and further the task T1 will not be allowed to access the resource again until every other task sharing the resource has finished accessing the resource. Therefore, the order of frame addresses in the request FIFO corresponds to the order of
20 commands in the command FIFO, allowing the channel to accurately match the frame addresses with the commands. No special tag is needed to establish this match, and the match is established using FIFOs, which are simple data structures.

25 In some embodiments, a processor executes several tasks processing network data flows. The processor uses pipeline and task-switching techniques described above to provide high bandwidth.

Other embodiments and variations are described below. The invention is defined by the appended claims.

BRIEF DESCRIPTION OF THE DRAWINGS

5 Fig. 1 is a block diagram of a system including a processor according to the present invention.

Fig. 2 is a block diagram illustrating resources in the system of Fig. 1.

10 Figs. 3A, 3B are timing diagrams illustrating data frame processing in the system of Fig. 1.

Fig. 4 is a logical diagram illustrating how different tasks access shared resources in the system of Fig. 1.

15 Fig. 5 is a block diagram of a processor used in the system of Fig. 1.

Fig. 6 illustrates an instruction execution pipeline of the processor of Fig. 5.

Figs. 7-12 illustrate task and resource state transitions in the system of Fig. 1.

20 Fig. 13A, 13B are block diagrams of task control block circuitry of the processor of Fig. 5.

Fig. 14 is a memory map for the system of Fig. 1.

Fig. 15 is a data area memory map for the system of Fig. 1.

25 Fig. 16 is a register file map for the processor of Fig. 1.

Fig. 17 is a data memory map for the processor of Fig. 1.

30 Fig. 18 illustrates address generation for the data memory of Fig. 17.

Fig. 19 illustrates tree nodes in the address resolution database used by the system of Fig. 1.

DESCRIPTION OF PREFERRED EMBODIMENTS

5 Fig. 1 illustrates a port interface (PIF) circuit 110 including a pipelined multi-tasking processor (microcontroller) 160. Port interface 110 includes four full-duplex ports that provide an interface between ATM switch 120 and respective four Ethernet segments (not shown) each of which is connected to a corresponding MAC 130.0-130.3. In each port "x" (x=0,1,2,3) the data between the Ethernet segment and the ATM switch 120 flows through a corresponding MAC 130.x and a corresponding slicer 140.x. The slicer 15 performs the well-known ATM SAR function, segmenting the Ethernet frame into ATM cells and appending ATM headers to the cells on the way to ATM, and assembling the frame from the cells on the way to the Ethernet. In some embodiments, the ATM switch interface to PIF 20 110 operates in frame mode in which the ATM switch transmits a frame of cells to a slicer 140 with no intervening cells. Slicers 140 use the AAL-5 protocol. The frame mode is described, for example, in U.S. patent application 08/706,104 "Cell Queuing in ATM 25 Switches" filed August 30, 1996 by A. Joffe et al. See also PCT application PCT/US97/14821 filed August 28, 1997 and incorporated herein by reference.

Other embodiments of PIF 110 provide interface between other networks, not necessarily ATM or

Ethernet. In some embodiments, the slicers 140 are replaced by suitable MACs.

In addition to performing protocol transformations (e.g. ATM/Ethernet transformations), PIF 110 can
5 perform IP routing, layer-2 switching, or other processing as determined by the software executed by the PIF microcontroller 160. See the description below in connection with Figs. 3A, 3B. See also U.S. patent application "SYSTEMS AND METHODS FOR DATA
10 TRANSFORMATION AND TRANSFER IN NETWORKS", attorney docket number M-4855 US, filed by A. Joffe et al. on the same date as the present application and incorporated herein by reference.

PIF 110 has high throughput even at modest clock
15 rates. Thus, in some embodiments, PIF 110 can perform IP routing for four 100 MB/sec Ethernet ports and respective four 155 MB/sec ATM ports at a clock rate of only 50MHz.

In Fig. 1, the data flow between each slicer 140.x
20 and the corresponding MAC 130.x is controlled by a corresponding channel 150.x (also called channel "x" below, i.e. channel 0, 1, 2 or 3). The channels 150 executes commands from microcontroller 160. In some
25 embodiments, the four channels 150.x are implemented by a single channel circuit that performs the function of the four channels 150 using time division multiplexing. See the aforementioned U.S. patent application attorney docket number M-4855 US, "SYSTEMS AND METHODS FOR DATA
TRANSFORMATION AND TRANSFER IN NETWORKS" incorporated
30 herein by reference.

The channels, the microcontroller, the slicers 140 and the MACs 130 communicate through memory 164 which includes internal memory ("frame and command memory") 170 and FIFOs 230, 240 described below.

5 In some Ethernet embodiments, the microcontroller is connected to MII (media independent interface) management circuit 180 connected to the Ethernet physical layer devices known in the art.

Search machine (SM) 190 maintains an address
10 resolution database in memory 200 to do IP routing or other processing as determined by the software. SM 190 also maintains databases in memory 200 that restrict the network connectivity (e.g. by defining VLANs or access control lists). The search machine is able to
15 search for a key (e.g. an Ethernet or IP address) presented to it by the microcontroller 160, and execute a learning algorithm to learn a layer-2 or layer-3 address if the address is not in the database. While search machine 190 is not software programmable in some
20 embodiments, the search machine supports flexible database node structure allowing the search machine to be easily adapted to different functions (e.g. IP routing, layer-2 switching). Search machine 190 executes commands from the microcontroller, such as
25 Search, Insert, Delete, etc. The search machine also provides the microcontroller with direct access to memory 200. The search machine is described in Addendum 8.

In some embodiments, memory 200 is implemented
30 using synchronous static RAMs in flow through mode of

operation. Multiple banks of memory are used in some embodiments.

In some embodiments, PIF 110 is an integrated circuit. Memory 200 is called "external" because it is not part of the integrated circuit. However, in other
 5 embodiments, memory 200 is part of the same integrated circuit. The invention is not limited by any particular integration strategy.

PIF 110 is also connected to a serial read only
 10 memory (ROM) 204 (serial EPROM in some embodiments) to allow the software ("firmware") to be loaded from ROM 204 into the microcontroller at boot time.

Fig. 2 illustrates a single channel 150.x and associated FIFO resources in memory 164. The channel
 15 is divided into two similar parts: ingress sub-channel 150I that controls the data flow from the corresponding MAC 130 to the corresponding slicer 140; and egress sub-channel 150E that controls the data flow from slicer 140 to MAC 130. In reference numerals, suffix
 20 "I" indicates circuits belonging to the ingress sub-channel, and suffix "E" indicates circuits belonging to the egress sub-channel, unless noted otherwise.

In each sub-channel 150I, 150E the data processing includes the following steps:

- 25 (1) The corresponding input control block 210 (i.e. 210I or 210E) stores the incoming data in the corresponding data FIFO 220. When sufficient portion of a data frame has been received to enable the microcontroller to start address translation or other
 30 processing (e.g., when the IP address and hop count

have been received in IP routing embodiments), input control 210 writes a request to respective request FIFO 230. The number of frame bytes received before the request is written to FIFO 230 is defined by

- 5 microcontroller-writable registers as described in the aforementioned US patent application attorney docket number M-4855 US.

- (2) Microcontroller 160 reads the request, reads appropriate parameters (for example, the source and destination addresses on the ingress side or the VPI/VCI on the egress side) from the corresponding data FIFO 220, and performs appropriate processing. The microcontroller uses the search machine 190 as needed to perform, for example, address resolution searches.

- 15 (3) When the search machine 190 has returned the search results to microcontroller 160, the microcontroller writes one of more channel commands to respective command FIFO 260 which specifies how the frame is to be transferred to the output device (MAC 130 or slicer 140).

- (4) After the entire frame was received, the input control 210 writes status information to respective status FIFO 240. The status FIFO is read by microcontroller 160. If the status shows that the frame is bad (for example, the checksum is bad), the microcontroller writes to command FIFO 260 a "discard" command to cause the output control 250 to discard the frame.

Steps (2), (3) and (4) may involve other processing described below in connection with Figs. 3A, 3B.

(5) Output control 250 executes commands from
5 respective command FIFO 260.

In some embodiments, data FIFOs 220 and command FIFOs 260 are stored in internal memory 170. Request FIFOs 230 and status FIFOs 240 are stored in memory 230, 240 (Fig. 1).

10 The outputs of egress output control blocks 250E are connected to the microcontroller to enable the ATM switch 120 to load programs ("applets") into the microcontroller for execution. The applets are first transferred to the egress side similarly to other
15 frames, but their VPI/VCI parameters indicate the microcontroller. Hence, the applets are not transferred to MACs 130. Instead, the applets are loaded from the output of circuits 250E to the microcontroller program memory 314 (Fig. 5) by a DMA
20 transfer.

Microcontroller 160 can also generate its own frames, write them to any data FIFO 220, and write commands to the corresponding command FIFO 260. The corresponding output control 250 will transfer the
25 frames as specified by the commands.

The microcontroller can also write command FIFOs 260 with commands to transfer statistics information stored in a separate memory (not shown) for each sub-channel 150I, 150E.

In some embodiments, microcontroller 160 is an expensive resource. Of note, in some embodiments the microcontroller instruction execution unit (shown at 310 in Fig. 5 and described below) accounts for about 70% of the gate count of PIF 110. Therefore, it is desirable to fully load the microcontroller. Full loading is achieved by appropriate multi-tasking as follows.

The microcontroller executes four "hardware tasks" HT0, HT1, HT2, HT3, one for each port 0, 1, 2, 3. The hardware tasks are executed in time division multiplexing manner as shown in the following table:

Table 1

Clock Cycle	1	2	3	4	5	6
Hardware Task	HT0	HT1	HT2	HT3	HT0	HT1

If a hardware task is not available (because, for example, it is waiting for the search machine), no microcontroller instruction is started in the respective clock cycle.

Each hardware task includes one or more software tasks. Each software task contains code that processes an entire frame. Since a frame on the ingress side and a frame on the egress side can arrive in parallel, in some embodiments each hardware task includes at least two software tasks to allow parallel processing of at least two frames. In some embodiments, different software tasks are provided for the ingress and egress sides. When an ingress software task cannot execute

due, for example, to the microcontroller waiting for the search machine, the microcontroller can execute the egress software task, and vice versa.

Below, the term "task" means a software task
5 unless we specifically recite a "hardware task".

Fig. 3A illustrates layer-3 processing of a single frame by an ingress task. At stage 290DA, the microcontroller reads from the frame the Ethernet (MAC) destination address DA at sub-stage 290DA.1. The
10 microcontroller supplies the address to search machine 190, which performs the search at sub-stage 290DA.2.

At sub-stage 290DA.3, the microcontroller examines the search results. If the DA was not found, the frame will be dropped or broadcast. If the DA was found and
15 the search machine recognized the DA as an address of a final destination station, the search results will include the VPI/VCI of the virtual connection (VC) on which the frame is to be transmitted to the final destination. In that case, the IP stage 290IP will be
20 skipped. If the search results indicate that the DA is an address assigned to an IP routing entity, IP processing is performed at stage 290IP.

At that stage, the microcontroller reads the IP destination address from the frame at sub-stage
25 290IP.1. The search machine performs a search on that address at stage 290IP.2. The microcontroller examines the search results at sub-stage 290IP.3. The results include the VPI/VCI and, possibly, access control restrictions. At sub-stage 290IP.3, the
30 microcontroller matches the access control restrictions

with the IP source address to determine if the frame is allowed. If not, the frame will be dropped.

At stage 290SA, the Ethernet source address SA is processed to implement an address learning algorithm and also to implement VLANs. More particularly, at sub-stage 290SA.1, the search machine performs a search on the SA. The search machine inserts or amends the SA data if required by the learning algorithm. At sub-stage 290SA.2, the search machine returns the VLAN to which the SA belongs. At sub-stage 290SA.3, the microcontroller compares that VLAN with the DA VLAN returned by the search machine at stage 290DA.2. If the Ethernet source and destination addresses belong to different VLANs, the frame is dropped.

At one or more of sub-stages 290DA.3, 290IP.3, 290SA.3, the microcontroller writes commands to the command FIFO 260I for the respective data flow (i.e. respective sub-channel). The commands may instruct the channel 150 to drop the frame, or to forward the frame to respective slicer 140. If the frame is forwarded, the channel may supply the VPI/VCI to the slicer and, possibly, increment to IP hop count and/or replace the source address with the address of respective MAC 130, as directed by the commands.

Fig. 3B illustrates processing performed by an egress task for a single frame. At stage 294VC, the task examines the VPI/VCI to determine if the frame is an applet. If so, the task loads the frame into the microcontroller program memory (shown at 314 in Fig. 5

described below) and executes the applet. Stage 294IP is skipped.

Alternatively, the VPI/VCI may indicate that the frame is an information request from ATM switch 120.

5 Examples of such requests include a request to read a register in PIF 110, or to read statistics information. The egress task performs the request. If this is a request for information, the egress task writes one or more commands to ingress command FIFO 260I of the same
10 hardware task that executes the egress task. These commands will cause the channel to send the information to the switch. Stage 294IP is skipped.

If the VPI/VCI does not indicate any management request (such as a request for information) from switch
15 120, stage 294IP is performed. At sub-stage 294IP.1, the task (i.e., the microcontroller) reads the IP destination address from the frame and supplies the address to the search machine. At stage 294IP.2, the search machine performs the search and returns the
20 Ethernet destination address and, possibly, access control information. At stage 294IP.3, the task writes commands to its egress command FIFO 260E to replace the Ethernet destination address of the frame with the address provided by the search machine, to replace the
25 Ethernet source address with the address of the respective MAC 130.x, and to transfer the frame to the MAC. Other kinds of processing may also be performed depending on the task software.

While the microcontroller waits for the search
30 machine at stages 290DA.2, 290IP.2, 290ISA.2, 294IP.2,

the microcontroller is available to execute another software task in the same or other hardware tasks.

In some embodiments, having a single task for each ingress flow and each egress flow does not fully load the microcontroller, and therefore more than one task for each half-duplex data flow are provided to enable the microcontroller to process more than one frame in each data flow in parallel. This is illustrated by the following considerations. The demands on the of microcontroller speed are the greatest when the Ethernet frames are short, because the same processing of Figs. 3A, 3B has to be performed both for short and long frames. The shortest Ethernet frame has 64 bytes. Suppose for example that the four Ethernet ports are 100 MB/sec ports and the ATM ports are 155 MB/sec. At 100 MB/sec, the shortest frame goes through the Ethernet port in 5.12 microseconds. Therefore, the microcontroller and the search machine have to process the frame in $5.12 + 1.6 = 6.72$ microseconds (1.6 microseconds is the interframe gap).

Let us assume a microcontroller clock speed of 50 MHz. This is a fairly slow clock speed to ensure reliable operation. Higher speeds (for example, 100 MHz) are used in other embodiments. At 50 MHz, the 6.72 microseconds is 336 clock cycles. Therefore, the clock cycle budget for the ingress and egress tasks of a single hardware task is $336/4 = 84$ clock cycles.

Since processing of a frame is divided between the microcontroller and the search machine, which do not necessarily work in parallel on the same frame, the

processing latency for one ingress frame and one egress frame in the same hardware task is allowed to be greater than 84 cycles even in wire speed processing. If processing takes more than 84 cycles, and 64-byte frames arrive back to back on the ingress and egress sides, the next frame may start arriving before the previous frame in the same data flow has been processed. Therefore, it is desirable to allow the microcontroller to start processing the next frame before the processing of the previous frame in the same data flow is completed. To implement such parallel processing of multiple frames in the same data flow, more than one software task for each data flow is provided.

Thus, in some embodiments, each hardware task HTx includes two ingress tasks IGx.0, IGx.1 and two egress tasks EGx.0, EGx.1. For example, hardware task HT1 includes ingress tasks IG1.0, IG1.1 and egress tasks EG1.0, EG1.1. Each task is identified by a 4-bit task number including:

CHID--channel ID (2-bits) = 0, 1, 2 or 3 for respective ports 0, 1, 2, 3;

SN--sequence number (0 for IGx.0, EGx.0; 1 for IGx.1, EGx.1);

I/E--0 for ingress; 1 for egress.

The total number of tasks is thus 16.

A frame is processed by a single task. If the frame is an applet, the applet is executed by the same task.

The microcontroller instruction execution is pipelined. Thus, Table 1 above indicates clock cycles in which a new instruction is started for the respective hardware task. For example, in cycle 1,
 5 instruction execution is started for hardware task HT0. The instruction execution continues in subsequent cycles.

Task access to FIFOs 230, 240, 260 in each sub-channel is controlled as shown in the logic diagram of
 10 Fig. 4. In Fig. 4, "Task 0" and "Task 1" are the two tasks for the same sub-channel, for example, ingress tasks IG1.0, IG1.1 for sub-channel 150I of channel 150.1. At the beginning, only Task 0 has access to the sub-channel FIFOs 230, 240, 260. When Task 0 accesses
 15 the request FIFO 230, switch "a" is flipped to connect the request FIFO to Task 1. Task 0 will not be allowed to read the request FIFO again until Task 1 has read the request FIFO.

Switch "b" controls the task access to command
 20 FIFO 260. Switch "b" is flipped when all the commands for a frame have been written by Task 0.

Switch "c" which controls the task access to status FIFO 240 is flipped when the status FIFO has been read by Task 0.

25 To synchronize task access to the search machine, search machine 190 executes commands one after another providing results in the same order.

Selecting a task for execution takes only one clock cycle (pipeline stage TS in Fig. 6 described
 30 below) in each instruction. Further, the task

selection is pipelined, and hence does not affect the throughput. The task selection is performed by hardware. No operating system is used in the microcontroller. Therefore, low latency is achieved.

5 At any time, each task is in one of the three states, Active, Ready, or Suspended. In the Active state, the task is being executed. At most four tasks (one for each hardware task) may be Active at the same time. Each Active task is scheduled for execution once
10 every four clock cycles (see Table 1 above).

 An Active task is transferred to the Suspended state if the task tries to access a resource that is unavailable. The resources are described in Addendum 2. When the resource becomes available, the task goes
15 to the Ready state.

 When an Active task is suspended, one of the tasks in the Ready state in the same channel is selected for execution by task control 320 (Fig. 5) and is transferred to the Active state.

20 Fig. 5 is a block diagram of microcontroller 160. Execution unit 310 executes programs stored in program memory 314. Programs are downloaded from ROM 204 (Fig. 1) during boot. In addition, applets can be loaded and executed dynamically as described above. The applets
25 can be discarded after being executed, or they can remain in memory 314.

 Execution unit 310 includes a register file 312 having general purpose registers, a special registers block 315, and a data memory 316. Register file 312
30 includes two 32-bit outputs connected to respective

buses sa_bus, sb_bus, which in turn are connected to inputs of ALU 318. 32-bit outputs of data memory 316 and special registers block 315 are connected to sa_bus. Separately connected to bus sa_bus are the
 5 outputs of special registers "null" and "one" (Table A6-1, Addendum 6) that store constant values (these registers are marked "Constant regs" in Fig. 5).

Bus sa_bus also receives the immediate field "imm" of an instruction read from program memory 314.

10 The 64-bit output of ALU 318 is connected 64-bit bus res_bus which is connected to inputs of register file 312, data memory 316, and special registers block 315.

Register file 312, data memory 316 and special
 15 registers 315 are described in Addendum 6. As described therein, the registers and the data memory are divided between tasks so that no save/restore operation is needed when tasks are rescheduled. In particular, special registers 315 include 16 PC
 20 (program counter) registers, one for each task.

Load/store unit (LSU) 330 provides an interface between execution unit 310, search machine 190, and internal memory 170. LSU 330 queues load and store requests to load a register from memory or to store
 25 register contents in memory. LSU 330 has an input connected to res_bus and also has a 64-bit output rfi connected to an input of register file 312.

DMA block 340 has an input connected to the bus res_bus to allow execution unit 310 to program DMA 340.
 30 DMA 340 can load applets into the program memory.

Fig. 6 illustrates the instruction execution pipeline. The pipeline has seven stages:

- (1) Task Select (TS) stage t0. In this stage, an active task is selected for the respective channel 150.x by task control 320. In some embodiments, the task control block implements a fixed priority scheme: task IGx.0 has the highest priority, then IGx.1, then EGx.0, and then EGx.1.

In some embodiments, once a task is made active, it is not suspended simply because a higher priority task becomes ready to run. The lower priority task remains active until it tries to access an unavailable resource.

- (2) During the Fetch (F) stage t1, task control block 320 drives the active task number signal task#_t1 (same as tsk_taskNumt1 in Table A1-1, Addendum 1) to execution unit 310. Signal task#_t1 selects one of the 16 PC values in special registers 315.

If no task is active, task control block 320 asserts the "idle" signal to execution unit 310. The signal is shown as "tsk_idle" in Table A1-1. When "idle" is asserted, task#_t1 is "don't care", and instruction execution unit 310 executes a NOP (no operation) instruction in the remaining pipeline stages.

If "idle" is deasserted, the PC register value selected by task#_t1 in special registers block 315 is provided to program memory 314. The instruction pointed to by the selected PC is read out from the memory to execution unit 310.

(3) During the Decode (D) stage t2, the instruction is decoded by the execution unit.

(4) During the Read (R) stage t3, the instruction operands are read from register file 312 and/or special registers 315 and/or data memory 316 and presented to ALU 318.

Also at this stage, task control 320 generates the Suspend signal (tsk_susp in Table A1-1) on lead 410 (Fig. 5) as described in more detail below in connection with Figs. 7-13B. If the Suspend signal is asserted, the task is suspended, the instruction execution is aborted and the task's PC register is frozen. When a task is made Active later, the same instruction will be re-executed.

Also at this stage, execution unit 310 generates a Wait signal. If the Wait signal is asserted, the instruction execution is not completed and the PC register is frozen, but the task remains active, and the instruction will be executed again starting the next clock cycle. For example, if instruction 1 in Fig. 6 is delayed due to the Wait signal being asserted in cycle 3, the same instruction will be re-executed as instruction no. 5 starting in cycle 4.

The Wait signal is asserted when a condition blocking the instruction is likely to disappear by the time the same hardware task is scheduled again. The Wait conditions are described in Addendum 3.

If the Suspend and Wait signals are deasserted, the PC register is changed to point to the next instruction.

(5) During the Execution (E) stage t4, the instruction is executed.

(6) During the Write Back (WB) stage t5, the results of the execution stage are written to their destinations except if a destination is in register file 312.

(7) During the Write Registers (WR) stage, the results of the execution stage are written into the register file 312 if required.

Of note, the WR stage of each instruction (e.g. instruction 1, cycle 6) occurs before the R stage of the next instruction of the same hardware task (see instruction 5, cycle 7). Therefore, if, for example, instruction 5 uses the results of instruction 1, the results will be written to the register file or the special registers before the instruction 5 reads them in cycle 7.

As illustrated in Fig. 6, when an instruction is aborted (at the R stage), the pipeline does not have to be purged from other instructions that have already been started, because these instructions belong to other tasks (moreover, to other hardware tasks). For example, if instruction 1 has to be aborted, the only other instructions that have been started on or before the R stage of instruction 1 are instructions 2, 3 and 4. These instructions do not have to be purged because they are executed by other tasks.

For a given hardware task, switching between the corresponding four software tasks does not require execution of separate instructions as would be the case

if task switching were performed by operating system software. High throughput is therefore achieved.

Fig. 7 is a bubble diagram illustration of task synchronization with respect to a single request FIFO 230 or status FIFO 240. In the bottom diagram 704, "Task 0" and "Task 1" have the same meaning as in Fig. 4. More particularly, these are the two software tasks sharing the request or status FIFO. In some embodiments, Task 0 is IGi.0 for the ingress sub-channel, or EGi.0 for the egress sub-channel.

Diagram 704 is a state machine illustrating the FIFO ownership. On RESET, the FIFO is owned by Task 0, as indicated by state 710RS.0.

When Task 0 has successfully read the FIFO, the FIFO becomes owned by Task 1, as indicated by state 710RS.1. Reading the FIFO is equivalent to flipping the "a" or "c" switch of Fig. 4. When Task 1 has successfully read the FIFO, the state machine returns to state 710RS.0.

The FIFO reading operation is indicated by condition mfsel[x] & ffrd. The signal mfsel is described in Addendum 4. The signal ffrd is asserted by the execution unit in stage t3 when any request or status FIFO is read by the microcontroller. A separate ffrd version is generated for each request and status FIFO. (If the FIFO read is successful, signal mfrd of Addendum 4 is asserted in stage t5.)

There are 16 request and status FIFOs. Each of these FIFOs is identified by a unique number "x" from 0 to 15. When the FIFO "x" is being read, the number "x"

is driven on lines mfsel, as indicated by mfsel[x] in Fig. 7.

Diagrams 720 and 740 indicate how Tasks 0 and 1 change states with respect to the FIFO. As indicated above, each task has three states: Ready ("RDY"), Active and Suspended. On RESET, all the tasks become Ready. A task becomes Active if selected at pipeline stage t0.

In the embodiment being described, a task cannot go from the Active state to the Ready state directly, though this is possible in other embodiments.

In the embodiment being described, each task goes from the Active state to the Suspend state on a "Suspend" condition 730. A suspended task becomes Ready on a release condition 734. The possible suspend conditions are listed in Table A1-2 of Addendum 1. The release conditions are listed in Table A1-3.

In diagram 720, the suspend condition 730 occurs when Task 0 attempts to access the FIFO when the FIFO is not available. More particularly, the condition 730 is:

- (1) the task is in pipeline stage t3 (indicated by signal "T3" generated by execution unit 310);
- (2) ffrd is asserted indicating a FIFO read operation;
- (3) mfsel identifies the FIFO "x"; and
- (4) either the FIFO is owned by Task 1 (state machine 704 is in state 710RS.1), or signal cfifordy[x] is low indicating that the FIFO "x" is empty. (Signal

cfifordy is described in Addendum 4. This signal is sampled every fourth cycle and is valid when sampled.)

The fact that the FIFO is being read by Task 0 and not by any other task is established by Task 0 being in pipeline stage t3.

Condition 730 for Task 1 (diagram 740) is similar.

Conditions 730 in diagrams 720, 740 are shown in Table A1-2 (Addendum 1) separately for each type of task (ingress task 0, ingress task 1, egress task 0, egress task 1) and each type of FIFO (request and status). The request FIFO conditions are listed as conditions number 1 in each of the four sections "Ingress Task 0", "Ingress Task 1", "Egress Task 0", "Egress Task 1". Thus, for ingress task 0, the condition is:

```
exe_RfifoRd & mfsel[x] & (Ireqf|~cfifordy[x])
```

Signal exe_RfifoRd is the same as ffrd. Ireqf indicates that the FIFO is owned by Ingress Task 1. All the signals in Table A1-2 are sampled in stage t3, so "t3" is omitted from some of the conditions in the table. For egress task 0, signal Ereqf indicates the respective request FIFO is owned by egress tasks 1. Thus, Ereqf replaces Ireqf. Task control 320 generates a separate signal Ireqf or Ereqf for each request FIFO. In Addendum 1, the signal negation is indicated by "~" before the signal name (as in ~cfifordy) or by the underscore following the signal name (as in Ereqf_ in condition 1 for egress task 1).

For the status FIFOs, the suspend conditions 730 are conditions numbered 2 in table A1-2. Signal

exe_SfifoRd is the ffrd version for a status FIFO. The number identifying the status FIFO is shown as "y" rather than "x".

Release condition 734 in diagram 720 is: Task 0
 5 owns the FIFO (state machine 704 is in state 710RS.0), and cfifordy[x] is high indicating that the FIFO is not empty. The release condition 734 for task 1 (diagram 740) is similar.

The release conditions are shown in Table A1-3 in
 10 Addendum 1. Each release condition corresponds to the suspend condition in the same slot in Table A1-2. For example, release condition 1 in section "Ingress Task 0" in Table A1-3 releases the task to the Ready state if the task was suspended by suspend condition 1 in
 15 section "Ingress Task 0" in Table A1-2. Thus, release conditions 1 and 2 in Table A1-3 correspond to the release conditions 734 in diagram 720 and 740 for the request and status FIFOs.

Fig. 8 illustrates task synchronization in an
 20 ingress sub-channel with respect to the sub-channel command FIFO 260 (i.e. 260I). Bottom diagram 804 illustrates the state machine for the ingress command FIFO. The FIFO can be owned both by the ingress and the egress tasks. On RESET, the state machine is in a
 25 state S0. In this state, the FIFO is owned by Ingress Task 0. When Ingress Task 0 writes to the FIFO a single word without locking the FIFO (flipping the switch "b" in Fig. 4), the FIFO moves to state S1 in which the FIFO is owned by Ingress Task 1. The writing
 30 operation is indicated by signal IcndFifoWr[x], where

"x" identifies one of the four ingress and egress tasks that can write the ingress command FIFO. (If IcmdFifoWr[x] is asserted by the execution unit in stage t3, the corresponding mload bit (Addendum 4) is asserted in stage t5.) Signal IcmdFifoWr[x] is asserted for an appropriate "x" whenever a respective task writes the FIFO.

The absence of locking is indicated by the "unlock" signal generated by execution unit 310 from the L flag of microcontroller instruction "CMD" (Addendum 7) used to write the command FIFOs.

When Ingress Task 1 writes a command FIFO (as indicated by IcmdFifoWr[x] where "x" indicates ingress Task 1) without locking the FIFO the state machine returns to state S0.

When Ingress Task 0 writes the FIFO in state S0 and the "lock" signal is asserted indicating that the FIFO is to be locked, the state machine moves to state S2. In that state, the FIFO is still owned by Ingress Task 0. The lock signal is generated by execution unit 310 from the L flag in microcontroller instruction CMD (Addendum 7). The FIFO remains in state S2 until Ingress Task 0 writes the FIFO with the "unlock" signal asserted. At that time, the FIFO moves to state S1.

Similarly, if Ingress Task 1 writes the FIFO in state S1 with "lock" asserted, the FIFO moves to state S3. In that state the FIFO is still owned by Ingress Task 1. The FIFO remains in state S3 until Ingress Task 1 writes the FIFO with "unlock" asserted. At that time, the FIFO moves to state S0.

When the state machine is in state S0 or S1, and an egress task writes the command FIFO without locking the FIFO, no state transition occurs. When egress task 0 writes the FIFO with locking in state S0, the FIFO
 5 moves to state S4. In that state, the command FIFO is owned by Egress Task 0. The state machine remains in state S4 until Egress Task 0 writes the command FIFO with "unlock" asserted. At that point, the state machine returns to state S0.

10 State S5 is similar to S4, but describe Egress Task 1 writing and owning the command FIFO.

States S6 and S7 are similar to respective states S4 and S5, but states S6 and S7 are entered from state S1 rather than S0.

15 Diagrams 820 and 840 illustrate state transitions of respective Ingress Tasks 0 and 1 with respect to the command FIFO. The suspend conditions 730 are conditions number 3 in Table A1-2. Signal
 IcmdFifoWr[x] is the same as exe_IcmdFifoWr[x] in
 20 conditions 3 for ingress tasks 0 and 1. Signal task#_t3 in Table A1-2 is the same as "T3" in diagrams 820 and 840. Signal ccmdfull[x] is a signal that the command FIFO "x" is full (see Addendum 4). This signal is valid in stage t3. Signal IcmdfOwnedByI0 indicates
 25 that the command FIFO is owned by ingress task 0 (that is, state machine 804 is in state S0 or S2). Signal IcmdfOwnedByI1 indicates that the command FIFO is owned by ingress task 1 (states S1, S3 in diagram 804).

For the egress tasks, the suspend conditions
 30 caused by writing to the ingress command FIFOs are

conditions 8 in Table A1-2. Signal `IcmdfOwnedByE0` indicates that the command FIFO is owned by egress task 0 (states S4, S6 in diagram 804). Signal `IcmdfOwnedByE1` indicates that the command FIFO is owned by egress task 1 (states S5, S3 in diagram 804).

The release conditions 734 (Fig. 8) are conditions 3 for the ingress tasks in Table A1-3.

The egress task synchronization with respect to the egress command FIFOs is similar. For the egress FIFOs, states S4, S5, S6, S7 are absent. In Tables A1-2 and A1-3, the pertinent conditions are conditions number 3. Signal `exe_EcmdFifoWr` replaces `exe_IcmdFifoWr` to indicate a write operation to the egress FIFO. Signal `Ecmdf1` indicates that the FIFO is owned by egress task 1.

Fig. 9 illustrates egress task synchronization with respect to the DMA resource. The bottom diagram 904 illustrates the DMA state machine. On RESET, the DMA is IDLE. When an egress task writes a DMA address (DMA transfer destination address in program memory 314) to the DMA address register DMAA (Addendum 6) of DMA 340 (Fig. 5), as indicated by "dmaa_wr" in Fig. 9, the task becomes the DMA owner, and the DMA 340 becomes active and starts the DMA transfer from internal memory 170. In the example of Fig. 9, the DMA owner is an Egress Task 0.

When the transfer has been completed, as indicated by "last_word" in Fig. 9, the DMA becomes ready ("RDY").

When the DMA is in the Ready state, and the DMA owner task reads the DMA address register (indicated by "dmaa_rd" in Fig. 9), the DMA moves to the Execute state. The DMA owner is allowed to read the address register only in the DMA Ready state. Non-owner tasks are allowed to read the DMA address register in any DMA state.

When the DMA is in the Execute state, the DMA owner task executes the applet loaded by the DMA. No new DMA access is allowed.

When the DMA owner task writes the release code 111 into the OP field of the DMAA register (Addendum 1), the DMA returns to the Idle state.

Diagrams 920, 930 illustrate state transitions for two egress tasks Task 0, Task N, not necessarily in the same hardware task. The conditions 730 are conditions 7 for the egress tasks in Table A1-2. In the table, exe_dmaaRd is the same as dmaa_rd in Fig. 9; exe_dmaaWr is the same as dmaa_wr. "dmaa_rd,wr" in Fig. 9 means "dmaa_rd OR dmaa_wr". Signals exe_dmaaRd, exe_dmaaWr are generated by execution unit 310.

Thus, the DMA owner task is suspended when it attempts either to read or write the DMA address register in stage t3 while the DMA is Active. The owner task is released when the DMA becomes Ready. The non-owner task is suspended when it attempts to write the DMA register in stage t3 while the DMA is Ready. The non-owner task is released when the DMA becomes Idle.

The release conditions 734 are indicated as "clast_word" in conditions 7 for egress tasks 0 and 1 in Table A1-2.

Fig. 10 illustrates task synchronization with respect to a semaphore register semr (Appendices 2, 6). The suspend conditions 730 are shown as conditions 5 in Table A1-2. Each suspend condition is as follows:

- (1) the task is in pipeline stage t3, and (2) a BITC or BITCI instruction is executed by the task with the target operand being the semaphore register, and the instruction has to be aborted because it is trying to write the same value to the semaphore register bit as the value the bit has had since before the instruction (this is indicated by signal exe_bitcSemReg in Table A1-2; all the signal names starting with "exe_" denote signals generated by execution unit 310). When the suspend occurs, task control block 320 sets a flag SPx to 1 where "x" is the task number (0-15).

The release condition 730 is that the flag SPx is cleared (i.e. set to 0). The task control block 320 clears all the flags SPx when any one of the following two conditions occurs:

- (1) in pipeline stage t3, an instruction BITC or BITCI is executed successfully by some other Task Y. This condition is indicated by signal exe_bitcSemAcc in release conditions 5 in Table A1-3.

- (2) The channel 150 writes the semaphore register. This is indicated by cstroke being asserted (Table A4-1 in Addendum 4) and csem[5] being at 1. The channel accesses the semaphore register to send an

indication to microcontroller 160 when commanded by a channel command. See the aforementioned U.S. patent application attorney docket No. M-4855 US "Systems and Methods for Data Transformation and Transfer in Networks" incorporated herein by reference.

Fig. 11 illustrates task state transitions with respect to the search machine 190. Suspend condition 730 (conditions 4 in Table A1-2) is that both of the following conditions (1) and (2) are true:

- (1) the task is in pipeline stage T3, the task is executing an instruction writing a command to the search machine (signal `scmd_wr`, shown as `exe_scmdWr` in Table A1-2) or reading a result from the search machine (signal `sres_rd`, shown as `exe_scmdRd` in Table A1-2).
- See microcontroller instruction SMWR (search machine command write) in Addendum 7 and the description of registers `scmd`, `scmde` in Addendum 6.

- (2) the search machine resources are not available to the task, as indicated by the signal `task_ownbit[x]` being 0 ("x" is the task number). This signal is shown as `sm_task_ownbit` in Tables A1-1 and A1-2 in Addendum 1. The signals whose names start with "sm_" are generated by search machine 190. The search machine resources and suspend conditions are described in Addendum 2.

The release condition 734 is: the respective `task_ownbit[x]` is 1.

Fig. 12 illustrates task synchronization with respect to the free list of scratch buffers 1610 (Fig. 16 and Addendum 5) in memory 170. The suspend

condition 730 (conditions 6 in Table A1-2) is that all of the following are true:

- (1) The task is in pipeline stage t3;
- (2) The task is reading the internal free list register IFREEL (Addendum 6), as indicated by signal ifreel_rd generated by the execution unit. This signal is shown as exu_ifreelRd in Table A1-2. The IFREEL register is read to get a free buffer number.
- (3) The "no_free_buffers" ("no_free_buf") signal is asserted by the special registers block 315 to indicate no free buffers.

The release condition 734 is that either of the following three conditions becomes true:

- (1) cstrobe (Table A4-1 in Addendum 4) is asserted by channel 150 while and csem[5] is 0, indicating that the channel 150 is returning the scratch buffer 1610 identified by signals csem[4:0] to the internal free list;
- (2) signal IfreelWr (exu_ifreelWr in Table A1-3) is asserted by the execution unit, indicating that the microcontroller is writing to the IFREEL register (Addendum 6); this register is written with a number of a scratch buffer being freed;
- (3) signal IfreerWr (exu_ifreerWr) is asserted by the execution unit, indicating that the microcontroller is writing to the IFREER register.

Fig. 13A is a block diagram of task control block 320. Task control 320 includes four identical blocks of latches 1304.0, 1304.1, 1304.2, 1304.3. Latches 1304.0 store the information related to a hardware task

in pipeline stage t0 (TS). That information is provided to the inputs of latches 1304.1. Latches 1304.1 store information on the hardware task in pipeline stage t1. Similarly, latches 1304.2, 1304.3 store information on hardware tasks in respective stages t2, t3. The outputs of latches 1304.1 are connected to respective inputs of latches 1304.2. The outputs of latches 1304.2 are connected to respective inputs of latches 1304.3. The outputs of latches 1304.3 are used to determine whether the software task in pipeline stage t3 should be suspended, and are also used to determine the states of the software tasks for the respective hardware tasks, as described below.

All the latches are clocked by the same clock (not shown).

In each block 1304, latch 1320 stores the respective hardware task number HT# (same as CHID above). Latch 1322 stores the active software task number ST#=<SN, I/E> for the hardware task. If no task is active for the hardware task, the output of latch 1322 is "don't care."

Thus, the outputs of latches 1320, 1322 of block 1304.1 form the signal task#_t1 (Fig. 5), and the outputs of latches 1320, 1322 of block 1304.2 form the signal task#_t2. The outputs of latches 1320, 1322 of block 1304.3 are connected to the inputs of latch circuit 1360, whose output is connected to the input of latch circuit 1362. The output of circuit 1362 provides the signal task#_t5 (Fig. 5).

The output of latch 1320 of block 1304.3 is connected to the input of latch 1320 of block 1304.0.

Each block 1304 contains four latch circuits 1330, one for each of the four software tasks IGx.0 (also shown as "I0" in Fig. 13A), IGx.1 ("I1"), EGx.0 ("E0"), and EGx.1 ("E1"), wherein "x" is the hardware task number stored in respective latch 1320. Each latch circuit 1330 includes two latches 1330S, 1330C, shown for simplicity only for task E1. Circuit 1330S stores the task's state (i.e., Ready, Active or Suspended). Circuit 1330C stores the release condition 734 needed to transfer the task to the ready state. The release condition is stored in the form of an index from 1 to 7 (as in Table A1-3), or from 0 to 6. The indices of possible release conditions for each type of task (I0, I1, E0, E1) are shown in the left column in Table A1-3 in Addendum 1.

The information in latch 1330C is meaningful only if the state stored in the respective latch 1330S is "Suspended". For the ready and active states, the information in latch 1330C is "don't care".

Each block 1304 includes six latches 1350 which store the states of the six respective request, status and command FIFOs for the corresponding hardware task. Possible states are illustrated in diagrams 704 (Fig. 7) and 804 (Fig. 8) and described above.

The outputs of latch circuits 1330, 1350 of block 1304.3 are connected to next state and condition generator 1354. Circuit 1354 generates the next states of tasks and request, status and command FIFOs and also

next release condition values. These state and condition signals are provided via bus 1358 to the inputs of circuits 1330, 1350 of block 1304.0.

Fig. 13B shows the circuit 1354 in more detail.

5 In circuit 1354, resource next stage generator 1380 receives the request, status and command FIFO states from latch circuit 1350 of block 1304.3. Generator 1380 also receives all the signals described above in connection with diagrams 704 and 804 which can cause
10 state transition of any one of the resource, status and command FIFOs. Generator 1380 calculates the next states of the FIFOs in accordance with diagrams 704 and 804, and provides the next states to latch circuit 1350 of latch block 1304.0 in the same clock cycle t3.

15 The output of each latch circuit 1330 is connected to the input of respective circuit 1390. For simplicity, only the circuit 1390 for task E1 is illustrated in detail. For task E1, the release condition output of latch 1330C is connected to the
20 select input of a multiplexer 1394. The data inputs of multiplexer 1394 receive the seven possible release conditions 734 for task E1 (Table A1-3 section "Egress Task 1"). Each data input to multiplexer 1394 is a one-bit signal asserted if the corresponding release
25 condition is true, and deasserted if the condition is false.

The release condition signal selected by multiplexer 1394 (that is, the signal corresponding to the release condition stored in latch 1330C of block
30 1304.3) is provided to task next stage generator 1398.

Generator 1398 also receives the task's current state from latch 1330S and the Suspend signal on lead 410 from suspend logic and release condition generator 1401 described below. Task next stage generator 1398
 5 generates a signal A indicating whether the task remains suspended or, alternatively, whether the task can be made active in the same clock cycle. Signal A is generated according to the following table 2:

10

TABLE 2

State from latch 1330S	Release cond. from MUX 1394	Suspend signal on lead 410	A
Suspended	TRUE	don't care	Ready
	FALSE	don't care	Suspended
Ready	don't care	don't care	Ready
Active	don't care	TRUE	Suspended
		FALSE	Active

Arbiter 1403 receives the A outputs from the four circuits 1390 and generates from them the following signals on bus 1358: (1) the next stage of each task
 15 for respective latches 1330S of block 1304.0; and (2) the active software task number ST# on lead 1404. The software task number is delivered to latch 1322 of block 1304.0.

Arbiter 1403 also generates the signal "idle"
 20 which is asserted to indicate that no task is active (see also Fig. 5).

Each circuit 1390 for tasks I0, I1, E0 includes the signal A generation logic identical to multiplexer

1394 and task next state generator 1398 for task E1, except that the release condition inputs to the multiplexers are taken from the sections of Table A1-3 which correspond to the respective tasks (Ingress Task 5 0, Ingress Task 1, or Egress Task 0).

Suspend logic and release condition generator 1401 receives the outputs of latch circuits 1350 of block 1304.3 and also receives all the signals (e.g. cfifordy, mfsel, etc.) needed to calculate the suspend 10 conditions 730 (Fig. 7-12 and Table A1-2 of Addendum 1). Block 1401 calculates the suspend conditions for an active task identified by the output of latch 1322 of block 1304.3. Suspend logic 1401 provides the suspend signal on lead 410 to task next state generator 15 1398 and to similar generators in the other three circuits 1390.

In addition, suspend logic 1401 generates the release condition data inputs 734 for each multiplexer 1394 and similar multiplexers (not shown) in the other 20 3 blocks 1390. The release conditions are generated according to the formulas of Table A1-3.

Further, suspend logic 1401 receives the state outputs of all the state latches 1330S in block 1304.3. For each task, if: (1) the state output indicates the 25 active state, and (2) one of the suspend conditions for the task is TRUE, suspend logic 1401 generates the index 734_in of the release condition needed to make the task ready. A separate index 734_in is generated for each task according to the respective section in

Table A1-3. Fig. 13B shows the index 734_in for task E1 only.

In all the other cases (that is, if the state output for the task is not "active" or the state output is active but no suspend condition for the task is TRUE), the release index 734_in for the task is "don't care".

The release index 734_in for task E1 is provided to a data input of multiplexer 1406. The other data input of the multiplexer receives the condition output from latch 1330C of block 1304.3 for task E1. The select input receives the "act" bit from state output of latch 1330S of block 1304.3 for task E1. The state output has two bits. The bit "act" is one of the two bits. The bit "act" indicates whether the state is "active". If "act" indicates the active state, multiplexer 1406 selects the release index 734_in. If "act" indicates a non-active state, multiplexer 1406 selects the output of condition latch 1330C. The selected signal is provided to bus 1358 which supplies the signal to latch 1330C for task E1 in block 1304.0.

Similarly, each circuit 1390 for each task includes a similar multiplexer 1406 (not shown) which selects: (1) the release condition index 734_in for the respective task from suspend logic 1401 if the output "act" from the latch circuit 1330 of block 304.3 for the respective task indicates an active state, and (2) the condition output of latch 1330 of block 1304.3 for the respective task if "act" indicates a non-active

state. The selected condition index is provided to the input of the respective latch 1330 in block 1304.0.

In some embodiments, when one task is suspended, the registers having task-specific values are not saved. In particular, each task has its own PC register having the task PC and flags (see Addendum 6). Further, register file 312 is divided into eight banks. Each bank is dedicated to a pair of an ingress task and an egress task from the same channel. The software executed by the task pair is written so that there are no common registers between the pair. Hence, while the register file registers may store task-specific values, these registers do not have to be saved or restored.

The embodiments described herein do not limit the invention. In particular, the invention is not limited by the number of ports, or by ports being full- or half-duplex, or by any timing, signals, commands or instructions. In some embodiments, the microcontroller comprises multiple execution units having the pipeline of Fig. 6 or some other pipeline. In some embodiments, one or more microcontrollers comprise multiple execution units such as present in a super scaler or VLIW (very large instruction word) processor. In some embodiments, the microcontroller is replaced by a processor implemented with multiple integrated circuits. The term "task" as used herein includes processes and threads. Other embodiments and variations are within the scope of the invention, as described by the appended claims.

ADDENDUM 1**TASK CONTROL BLOCK****TABLE A1-1: Task Control Block signal list**

No.	Signal Name	Width	I/O	Tim- ing	Function
	SM 190 Interface				
1.	tsk_taskNumt2 [3:0]	4	O	t2	Task number during Decode Stage
2.	tsk_taskNumt5 [3:0]	4	O	t5	Task number during WB Stage
3.	sm_task_ownbit [15:0]	16	I	async	Task Own bit (1-resource available)
	Channel 150 Interface				
4.	ccmdfull[7:0]	8	I	async	Command FIFO Full
5.	cfifordy[15:0]	16	I	async	Req/Stt FIFO Ready
	Execution Unit Interface				
6.	tsk_susp	1	O	t4	Suspend indication
7.	tsk_taskNumt1 [3:0]	4	O	t0	Task Number
8.	tsk_idle	1	O	t0	Indication to inject NOP during Fetch
9.	exu_RfifoRd	1	I	t3	Req FIFO read
10.	exu_SfifoRd	1	I	t3	Stt FIFO read
11.	exu_scmdRd	1	I	t3	SM Result Read
12.	exu_scmdWr	1	I	t3	SM Command write
13.	exu_IcmdFifoWr	1	I	t3	Ingress Command FIFO write
14.	exu_EcmdFifoWr	1	I	t3	Egress Command FIFO write
15.	exu_lock	1	I	t3	Command FIFO lock indication
16.	edma_done	1	I	async	DMA done indication
17.	edma_busy	1	I	async	DMA Busy indication
18.	edma_suspend	1	I	t3	DMA suspend
19.	edma_sel	1	I	t3	DMA release select
20.	efs_flRelease	1	I	async	Free List Release Flag
21.	efs_semRelease	1	I	async	Semaphore Release Flag
22.	efs_suspend	1	I	t3	Semaphore or Free List suspend
23.	efs_sel	1	I	t3	Semaphore or Free List rel. select
24.	tsk_init_doneE 0	1	I	async	E0 Task Init
25.	tsk_init_doneI 0I1E1	1	I	async	I0, I1, E1 Task Init
	LSU Interface				
26.	ts_taskNum2	4	O	t2	Task number during

No.	Signal Name	Width	I/O	Tim- ing	Function
					Decode Stage

TABLE A1-2: Task Suspend Conditions

num	Suspend Conditions
Ingress Task 0	
1	exe_RfifoRd & mfsel[x] & (Ireqf ~cifordy[x])
2	exe_SfifoRd & mfsel[y] & (Isttf ~cifordy[y])
3	exe_IcmdFifoWr[x] & task#_t3 & (ccmdfull[x] ~ICmdOwnedByI0)
4	(exe_scmdRd exe_scmdWr) & task#_t3 & ~sm_task_ownbit[x]
5	exe_bitcSemRej & task#_t3
6	exu_ifreelRd & no_free_buf
Ingress Task 1	
1	exe_RfifoRd & mfsel[x] & (~Ireqf ~cifordy[x])
2	exe_SfifoRd & mfsel[y] & (~Isttf ~cifordy[y])
3	exe_IcmdFifoWr[x] & task#_t3 & (ccmdfull[x] ~ICmdOwnedByI1)
4	(exe_scmdRd exe_scmdWr0 & task#_t3 & ~sm_task_ownbit[x]
5	exe_bitcSemRej & task#_t3
6	exu_ifreelRd & no_free_buf
Egress Task 0	
1	exe_RfifoRd & mfsel[x] & (Ereqf ~cifordy[x])
2	exe_SfifoRd & mfsel[y] & (Esttf ~cifordy[y])
3	exe_EcmdFifoWr[x] & task#_t3 & (ccmdfull[x] ECmdf1)
4	(exe_scmdRd exe_scmdWr) & task#_t3 & ~sm_task_ownbit[x]
5	exe_bitcSemRej & task#_t3
6	exu_ifreelRd & no_free_buf
7	(exe_dmaaRd exe_dmaaWr) & task#_t3 & ~dma_idle
8	exe_IcmdFifoWr[x] & task#_t3 & (ccmdfull[x] ~ICmdOwnedByE0)
Egress Task 1	
1	exe_RfifoRd & mfsel[x] & (Ereqf_ ~cifordy[x])
2	exe_SFifoRd & mfsel[y] & (Esttf_ ~cifordy[y])
3	exe_EcmdFifoWr[x] & task#_t3 & (ccmdfull[x] ~ECmdf1)
4	(exe_scmdRd exe_scmdWr) & task#_t3 & ~sm_task_ownbit[x]
5	exe_bitcSemRej & task#_t3
6	exu_ifreelRd & no_free_buf
7	(exe_dmaaRd exe_dmaaWr) & task#_t3 & ~dma_idle
8	exe_IcmdFifoWr[x] & task#_t3 & (ccmdfull[x] ~ICmdOwnedByE1)

5

TABLE A1-3: Task Release Conditions

num	Release Conditions
Ingress Task 0	
1	Ireqf_ & cifordy[x]

num	Release Conditions
Ingress Task 0	
2	Isttf_ & cfifordy[y]
3	ccmdfull[x]_ & ICmdfOwnedByI0
4	sm_task_ownbit[x]
5	SPx & (exe_bitcSemAcc (cstrobe & csem[5]))
6	exu_ifreelWr exu_ifreerWr (cstrobe & ~csem[5])
Ingress Task 1	
1	Ireqf & cfifordy[x]
2	Isttf & cfifordy[y]
3	ccmdfull[x]_ & ICmdfOwnedByI1
4	sm_task_ownbit[x]
5	SPx & (exe_bitcSemAcc (cstrobe & ~csem[5]))
6	exu_ifreelWr exu_ifreerWr (cstrobe & ~csem[5])
Egress Task 0	
1	Ereqf_ & cfifordy[x]
2	Esttf_ & cfifordy[y]
3	ccmdfull[x]_ & ~ECmdf1
4	sm_task_ownbit[x]
5	SPx & (exe_bitcSemAcc (cstrobe & csem[5]))
6	exu_ifreelWr exu_ifreerWr (cstrobe & ~csem[5])
7	clast_word
8	ccmdfull[x]_ & ICmdOwnedByE0
Egress Task 1	
1	Ereqf & cfifordy[x]
2	Esttf & cfifordy[y]
3	ccmffull[x]_ & ECmdf1
4	sm_task_ownbit[x]
5	SPx & (exe_bitcSemAcc (cstrobe & csem[5]))
6	exu_ifreelWr exu_ifreerWr (cstrobe & ~csem[5])
7	clast_word
8	ccmdfull[x]_ & ICmdOwnedByE1

ADDENDUM 2

RESOURCES

All resources are accessed through special registers or dedicated microcontroller commands.

5 **Search Machine**

The Search Machine has two resources: Command, written by the microcontroller, and Result.

There are 16 write only Command resources (one for every task). The only case when this resource is not
10 available is when a previous command from the same task is not completed.

There are 16 read only Result resources (one for each task). When a command is posted to the Search Machine, the Result becomes unavailable until the
15 command is executed. Some commands (e.g. Insert or Delete) do not have a result.

Channel Control

The channel control has three kinds of resources: command FIFOs 260, request FIFOs 230, and status FIFOs
20 240.

A command resource is unavailable in two cases:

- a. The resource belongs to another task.

In this case when the other task releases the resource, it becomes available to this task.

- 25 b. Command FIFO is full. In this case when the Command FIFO becomes not full, the task can continue to use this resource.

The Command resource has session protection (i.e. several commands can be written by one task before the
30 resource is passed to another task). This is achieved

by locking the resource during the first access and unlocking it in the last access. When the Command resource is locked, no other task can access this resource.

- 5 An egress task EGx of a channel 150.x may write commands to an ingress command FIFO 260I of the same channel 150.x to send a message to switch 120. The egress task may write the ingress command FIFO whenever the ingress command FIFO is unlocked. When the egress
- 10 task writes its first command to the ingress command FIFO 260I, the command FIFO becomes locked until the last command from the egress task has been written.

A Request or Status FIFO resource is not available in two cases:

- 15 a. The resource belongs to another task. In this case when the other task reads the FIFO, the resource becomes available to this task.
- b. The FIFO is empty. In this case when the FIFO becomes ready, the task can continue to
- 20 use this resource.

DMA

- The DMA block is responsible for downloading applets from data FIFOs to the program memory 314. This resource is used by egress tasks which set the DMA
- 25 address before the transfer and read the last word address when the transfer is complete. Reading the last word address during the transfer will cause the task to be suspended until the last word is transferred. Also, an attempt to write a new DMA

address by another egress task, when the first transfer is not complete, will cause the task suspension.

Internal Memory 170 Management

The Internal Memory Management is responsible for managing free buffers 1610 (Fig. 15) inside the Scratch Pad Area in the internal memory. There are 32 free buffers in the memory. When a task wants to get the next available free buffer, it accesses the Free List (FreeL) resource (register IFREEL in Addendum 6). If there are no buffers left, the task will be suspended. The buffers are released back to the free list when a channel command which used this buffer indicates that the buffer is to be released.

Semaphore

The semaphore register semr has 32 bits. Each of them is directly accessible using the Bit Change Immediate (BITCI) and BITC commands of the microcontroller. The semaphores are used for protection and communication between tasks.

If the BITCI or BITC command attempts to write the same value to the bit as the current bit value, it will be aborted and its task will be suspended. Later on, when the semaphore register is changed (any bit in the register is changed), all tasks which are waiting for a semaphore will be made Ready and will try to execute the Bit_Change_Immediate command again.

Bits 31-24 of the semaphore register can be set by changing respective predetermined external pins (not shown) of PIF 110 from 0 to 1.

ADDENDUM 3

TASKS WAIT CONDITIONS

There are two conditions which may cause the Wait signal to be asserted:

5 **(1) Register Scoreboard**

For each register in the microcontroller there is a scoreboard bit which indicates its status. If the bit is set, the register is dirty, i.e. waiting for data to be loaded by the LSU 330. A possible scenario
10 is as follows:

(a) A task requests loading the register by the LSU.

(b) The task requests using this register as a source. However, the scoreboard is dirty. Hence, the
15 Wait signal is asserted.

(c) Then the LSU loads the register.

(d) The task again requests using this register as a source. This time the usage is permitted.

(2) LSU FIFO Full

20 This is another condition to generate the wait signal. Once the LSU FIFO that queues the load and store requests becomes ready this condition is cleared.

ADDENDUM 4

The following table lists some signals used in the channel/microcontroller interface. "I" means the signal is an input for the channel. "O" means the signal is a channel output.

TABLE A4-1

Signal name	Width	I/O	Function
Indication			
csem[5:0]	6	O	Semaphore ID; CSEM[5] = $\overline{\text{SCRATCH}}$ /NOP. Indication
cstrobe	1	O	Semaphore SET strobe
Command FIFO			
mflod[7:0]	8	I	CMD FiFo Load strobes (<Channel>, I/E)
ccmdfull[7:0]	8	O	CMD FIFO Full (<Channel>, I/E)
Req/Status FiFo			
cfifordy[15:0]	16	O	FIFO RDY (READY) (<Channel>, I/E, $\overline{\text{Req}}$ /Stt)
mf sel[3:0]	4	I	FIFO Select address (<Channel>, I/E, $\overline{\text{Req}}$ /Stt)
mfrd	1	I	FIFO Read Strobe

ADDENDUM 5MEMORYMap of Internal Memory 170

The internal memory map is shown in Fig. 14.

5 DATA AREA 1510 (ADDRESSES 0000-1FFF HEX)

This area is used for the Scratch Pad 1610 and the Data and Command FIFOs. This area is accessed using relative addresses. The data area memory map is shown in Fig. 15.

10 In Fig. 15, "DBASE_I" is the "DBASE" field of the CFGR register (described below) for the ingress side. Similarly, DLEN, CBASE, CLEN are fields of the corresponding CFGR register. The suffix "_I" stands for ingress, and "_E" stands for egress.

15

CONTROL AREA 1520 FOR EACH CHANNEL

One of the register types in this area is:

CFGR - Channel Configuration Register (Ingress & Egress)

20

There are 8 CFGR registers, one per direction of each channel. Their fields are:

DBASE	(9 bits)	Data Buffer Base Pointer (64 bytes aligned)
DLEN	(7 bits)	Data Buffer Length (64 bytes granularity)
CBASE	(9 bits)	Command Buffer Base Pointer (64 bytes aligned)
CLEN	(3 bits)	Command Buffer Length (64 bytes)

granularity)
GAP (4 bits) Minimum gap between Data Read and
Write pointers when the Frame Control
Word is invalid (8 bytes granularity)

DATA AREA 1530 (ADDRESS 4000-5FFF HEX)

This area is described in the aforementioned U.S.
patent application attorney docket number M-4855 US.

5

ADDENDUM 6

MICROCONTROLLER REGISTERS

Register File map

The register file 312 is divided into eight banks
5 (Fig. 16). Each bank is dedicated to a pair of ingress
and egress tasks from the same channel 150.x. In some
embodiments, the ingress task uses more registers than
an egress task because ingress processing is more
complex. In some embodiments, task software is such
10 that there are no common registers between the two
tasks.

Each register r0.0-r7.7 is 1 byte wide. 8
consecutive bytes can be read in parallel from the
register file. To form a 7-bit register address, the
15 register number (0 through 63) is concatenated with the
bank ID which itself is a concatenation of the channel
ID "CHID" and the task pair number SN (0 or 1); the
address MSB is 0 to indicate register file 312 (versus
special registers 314).

20 Microcontroller register map

All registers in the microcontroller are directly
accessible through microcontroller commands. The
register map is divided into two regions: register file
312 and special registers 315. A register address
25 consists of 7 bits. For the special registers 315, the
address MSB is 1; for the register file 312, the MSB is
0.

Data Memory 316

Data memory 316 (Fig. 17) is used for temporary storage of variables as well as for some parameters described below.

5 Data memory 316 is therefore divided into three regions:

- a. For each task, tasks registers tr0-tr5 (6 per task). These registers are dedicated to the respective task.
- 10 b. Channel registers cr0-cr3 (4 per channel 150.x). These registers are dedicated to a hardware task. All tasks of the same channel (two ingress and two egress tasks) have access to these registers.
- 15 c. Global registers gr (16 registers). These registers are global for all the tasks.

Data memory 316 is 128 words of 32 bits.

The 7-bit address generation scheme for data memory 316 is shown in Fig. 18, where:

- 20 tr is Task Register number (0-5).
- tn is Task Number (0-15) (tr and tn form a task register address).
- cr is Channel Register number (0-3; "110," cr, cn form a channel register address).
- 25 cn is Channel Number (0-3).
- gr is Global Register number (0-15).

Special registers (SR) 315 (see the table A6-1 below) are directly accessible through microcontroller commands (similar to the register file). Special
30 registers 315 may be divided into three types:

- a. registers which belong to a task, such as Program Counter (PC), Task Number (TIN), etc.
- b. resource registers, such as Request FIFO (reqf), Status FIFO (sttf), Search Machine Command (scmd), etc. (see Addendum 2).
- c. Data memory 316 registers, such as task registers (tr), channel registers (cr) and global registers (gr).

The resources and the data memory 316 (note types (b) and (c)) are mapped into the special registers to simplify their access.

Pertinent special registers are summarized in the following table.

TABLE A6-1: Special Registers

Address	name	type	access	width	total	comment
1000_000	null	-	r	32	--	zero data
1000_001	one	-	r	32	--	all ones data
1000_010	pc	a	rw	16	16	program counter
1000_011	tn	a	r	4	1	task number
1000_100	ctl	a	rw	16	1	general control register
1000_101	dmaa	a	rw	32	1	program download address
1000_110	reqf	b	r	16	8	request fifo
1000_111	sttf	b	r	16	8	status fifo
1001_000	imp	a	rw	10	16	internal memory pointer
1001_001	xmp	a	rw	16	16	external memory pointer
1001_100	cmd_i	b	w	64	fifo	ingress command
1001_101	cmd_e	b	w	64	fifo	egress command
1001_110	cmd_il	b	w	64	fifo	ingress command (lock)
1001_111	cmd_el	b	w	64	fifo	egress command (lock)
1010_000	scmd	b	rw	64	16	SM command/result
1010_001	scmde	b	rw	64	16	SM command/result extension

Address	name	type	access	width	total	comment
1010_010	xfreel	b	rw	16	4	external free list
1010_011	timer	a	rw	50	1	general timer
1010_100	smcntl	a	rw	17	1	search machine control reg.
1010_101	flcnt	a	r	17	4	external free list counter
1010_110	agel0	a	r	16	4	head of age list #0
1010_111	agell	a	r	16	4	head of age list #1
1011_000	semr	a	rw	32	1	semaphore reg
1011_001	ifreel	b	rw	5	1	internal free list
1011_010	ifreer	b	rw	32	1	internal free register
1011_011	miir	a	rw	32	1	mii register
1011_100	msgr	a	rw	32	1	message register
1011_110	thrshl0	a	rw	16	4	age threshold #0
1011_111	thrshl1	a	rw	16	4	age threshold #1
1100_iii	tr0-5	c	rw	32	96	task register
1101_0ii	cr0-3	c	rw	32	16	channel register
1101_111	pmdr	a	r	32	1	program memory data register
111i_iii	gr0-15	c	rw	32	16	general register

Register fields of some special registers are as follows:

PC - Program Counter & Flags

- 5 PC (10 bits) Program Counter
- G (1 bit) Flag - Greater
- L (1 bit) Flag - Less
- E (1 bit) Flag - Equal
- C (1 bit) Flag - Carry
- 10 G, L, E, and C are read-only.

TN - Task Number

- CHID (2 bits) Channel Id
- SN (1 bit) Sequence Number
- I/E (1 bit) Ingress(0)/Egress(1)

SCMD, SCMDE - Command and Command Extension

During write operations these 32-bit registers form a command for the search machine. During read operations these registers provide the result.

- 5 SCMDE should be written prior to SCMD.

XFREEL - External Free List

- A write to this register causes adding a block to the free list stack in external memory 200. A read from this register causes removing a block from the stack.
- 10

There is one free list stack per channel. Each register contains a 16-bit pointer to the top of the stack.

TIMER - general timer

- 15 Timer (32 bits) Timer value.
- The timer is a free running counter advanced every 8 system clock ticks.
- NXTE (16 bits) Pointer to the next entry to examine for aging.
- 20 This field is write only. Should be initialized after reset.
- ET (1 bit) Enable Timer Update.
- This field is used during write operations. If ET=1, the timer counter gets the value
- 25 being written. If ET=0, the timer counter is not affected by the write.
- EN (1 bit) Enable Next Entry Update. This field is used during write operations. If EN=1, the NXTE pointer gets the new value. If
- 30 EN=0, the NXTE field is invalid.

SMCNTL - Search Machine Control register

Pointer (16 bits) Node area start pointer.

This pointer defines the search node area (the bottom of this area is 0xFFFF). The
 5 automatic aging mechanism will be performed only inside this area.

AGE (1 bit) Aging Enable (0-disable; 1-enable).

FLCNT - Free list counter

This read only register contains the number of
 10 entries in the free list in the scratch pad area of memory 170.

Count (17 bits) Counter (max value is 0x10000)

AGELO, AGE11 - head of age list 0,1

These are read only registers (two per channel).
 15 Each contains the top of the age list (there are two age lists per channel). A read from any one of these registers causes the register to clear. Of note, the TSTMP (time stamp) field in the node (Addendum 8) is used to link nodes together in this list. When the
 20 register is 0, the list is empty.

Pointer (16 bits) Top of the List pointer.

THRSHL0, THRSHL1 - Threshold register

Each of these registers contains the threshold associated with the corresponding Age List.

25 When $|current_time - timestamp| > threshold$, and the entry is of type LRND (learned entry), the entry is added to the Age List.

threshold (16 bits) Threshold value

MSGR - Message Register is used to transfer messages
 30 between the microcontroller and switch 120 CPU (not

shown). The messages are transferred through the Header line.

MSGA (16 bits) Message to CPU when writing MSGR, and from CPU when reading the register. This field is cleared after read.

MSGB (16 bits) Message to CPU when reading the register (for testing).

DMAA - DMA Address

OP (3 bits) Operation

- 10 000- nop
- 001- Load from EPROM 204
- 010- Load from switch 120
- 111 - Release

EPA (13 bits) EPROM Start Address

15 LER (1 bit) Load Error

PMA (10 bits) Program Memory Address

SEMR - Semaphore Register

S[i] (1 bit) Semaphore bit "i"

IFREER - Internal Free Register (16 bits)

20 F[i] (1 bit) indicates whether Block "i" in the scratch pad area of memory 170 is free.

IFREEL - Internal Free List

BLKN (5 bits) Free Block Number (i.e. scratch buffer number; see Fig. 15). A read of this register removes the scratch buffer BLKN from the free list. A write to this register returns to the free list the buffer identified by the BLKN value being written.

MIIR - MII control register

This register is used to communicate with Ethernet PHY devices through MII control interface.

BSY (1 bit) Busy.

5 Set with a new command, and reset when the command is done.

CMD (4 bits) Command

 1000 - Scan On

 0000 - Scan Off

10 0100 - Send Control Info

 0010 - Read Status

NV (1 bit) Not Valid.

 Set when the data from PHY is not valid.

FIAD (5 bits) PHY Address.

15 RGAD (5 bits) Register Address.

Data (16 bits) Data.

ADDENDUM 7MICROCONTROLLER INSTRUCTIONS**Three Operand instructions**

These instructions perform arithmetic and logic
 5 operations between Operand_A and Operand_B. The result
 is written to Operand_C. The instructions are:

ADD - Add
 SUB - Subtract
 OR - Logical OR
 10 AND - Logical AND
 XOR - Logical XOR
 SHL - Shift Left
 SHR - Shift Right
 BITC - Bit Change

15 The instruction Size field specifies the operand
 sizes.

A two-bit "dt" field (destination type) in the
 instruction specifies the type of Operand_C as follows:

dt = 00 - Operand_C is a register in register
 20 file 312 or special registers 315.
 dt = 10 - Operand_C is in memory 170. The
 Operand_C field is used as 7 bits
 immediate value in the Load/Store Unit
 for address generation.
 25 dt = x1 - Operand_C is in external memory 200.
 The Operand_C field together with dt[1]
 bit is used as an 8 bit immediate value
 in the Load/Store Unit for address
 generation.

Note that instructions with non-zero dt cannot use resources as their operands.

Two operand instruction with an immediate byte

These instructions perform arithmetic or logic
5 operation between Operand_A and an immediate byte. The result is written to Operand_C. The instructions are:

ADI - Add Immediate
SBI - Subtract Immediate
ORI - Logical OR Immediate
10 ANDI - Logical AND Immediate
XORI - Logical XOR Immediate
SHLI - Shift Left Immediate
SHRI - Shift Right Immediate
BITCI - Bit Change Immediate

15 The Size field specifies the sizes of operands.

A two-bit "dt" field (destination type) of the instruction specifies the type of the Operand_C field as in the three-operand instructions.

Two operand instructions

20 These instructions perform move and compare operations between two operands. The instructions are:

MOVE - MOVE Operand A to Operand C
CMP - Compare Operand C to Operand A

The size field of the instruction specifies the
25 sizes of operands.

One operand instructions with Immediate

These instructions perform move and compare operations between an operand and an immediate field. The instructions are:

30 MVIW - MOVE Immediate Word

MVIB - MOVE Immediate Byte

CPIB - Compare Immediate Byte

CPIW - Compare Immediate Word

- 4 The size field of the instruction specifies the
5 size of Operand_C.

Special one operand instructions with immediate field

These instructions perform an operation on Operand C as follows:

- 10 SMWR - Search Machine Write
CMD - Channel Command Write
CASE - Case statement
BTJ - Bit Test and Jump

Load & Store Instructions

- These instructions perform Load and Store
15 operation between Operand A and memory 170 or 200. The instructions are:

LOAD

STORE

- The "dt" field (destination type) specifies the
20 type of destination as follows:

- dt = 10 - Destination is memory 170. The immediate field is used as a 7 bit immediate value in the Load/Store Unit for address generation.
- 25 dt = x1 - Destination is memory 200. The immediate field together with the dt[1] bit is used as an 8 bit immediate value in the Load/Store Unit for address generation.

- 30 **Special Immediate instruction**

This instruction is CMDI (Command Immediate). It is used to write to a command FIFO.

Selected Instructions

ADD, SUB, ADI, SBI

5 Flags:

E is set when result is equal to zero

C is set when Carry (for ADD, ADI) or Borrow (for SUB, SBI) is generated (based on operand opC size)

10 **OR, AND, XOR, SHL, SHR, ORI, ANDI, XORI, SHLI, SHRI**

Flags:

E is set when result is equal to zero

BITC -- Bit Change.

15 Operands: bits [31:25] = opC, [24:18] = opA, [17:16] = dt, [14:8] = opB, [7] = v

Operation: opC ← opA[opB] ← v (i.e. opC receives the value of opA except that the bit number opB in opC is set to v)

20 Flags:

E is set when (opA[opB] == v)

BITCI -- Bit Change immediate

Operands: bits [31:25] = opC, [24:18] = opA, [17:16] = dt, [12:8] = imm, [7] = v

25 Operation: opC ← opA[imm] ← v

Flags:

E is set when (opA[imm] == v)

CMP - Compare

Operands: bits [31:25] = opC, [24:18] = opA, [7:5] =

30 operand size

Operation: opC?opA

Flags:

E is set when (opC == opA)

G is set when (opC > opA)

5 L is set when (opC < opA)

CPIW - Compare immediate word

Operands: bits [31:25] = opC, [23:8] = imm

Operation: opC?imm

Flags:

10 E is set when (opC == imm)

G is set when (opC > imm)

L is set when (opC < imm)

CPIB - Compare immediate byte

Operands: bits [31:25] = opC, [23:16] = bit_mask,

15 [15:8] = imm

Operation: (bit_mask & opC)?imm

Flags:

E is set when ((bit_mask&opC) == imm)

G is set when ((bit_mask&opC) > imm)

20 L is set when ((bit_mask&opC) < imm)

LOAD -- Load from internal or external memory

Operands: bits [31:25] = aop, [24:18] = opA, [17:16] =
dt, [7] = i, [6] = f

Operation:

25 if [dt==10] opA<-IM[{aop,imp}]; imp=imp+i;

if [dt==x1] opA<-XM[{aop,xmp}]; xmp=xmp+i;

IM is internal memory 170; imp is the internal
memory pointer register (Table A6-1);

XM is external memory 200; xpm is the external
30 memory pointer register (Table A6-1).

When the f bit is set, the execution of load instruction is delayed if previous store operation from the same channel is not complete.

- 5 aop is address bits concatenated with imp or xmp ("{" indicates concatenation).

STORE -- Store to internal or external memory

Operands: bits [31:25] = aop, [24:18] = opA, [17:16] = dt, [7] = i

- 10 Operation:

if [dt==10] opA->IM[{aop,imp}]; imp=imp+i;

if [dt==x1] opA->XM[{aop,xmp}]; xmp=xmp+i;

IM, XM, imp, xmp, and aop have the same meaning as for the LOAD instruction.

- 15 **SMWR** -- Search Machine command Write

Operands: bits [31:25] = opC, [23:8] = imm

Operation: scmd<- {opC[63:16], imm}

CMDI -- Immediate Command to Channel

Operands: bits [31:8] = imm, [7] = L, [6] = P

- 20 Operation:

Command_port <- {40'b0, imm}

where 40'b0 denotes 40 binary zeroes.

if P=0, Command_port = cmd_i; (Ingress Command)

if P=1, Command_port = cmd_e; (Egress Command)

- 25 The instruction L flag (1 bit) is Lock/Unlock control (when set, the lock state in the instruction is changed)

CMD -- Command to Channel

Operands: bits [31:25] = opC, [23:8] = imm, [7] = L,

- 30 [6] = P

Operation:

Command_port <-{opC[63:16], imm}

if P=0, Command_port = cmd_i; (Ingress Command)

5 if P=1, Command_port = cmd_e; (Egress Command)

The 1-bit L flag in the instruction is Lock/Unlock control (when set, the lock state is changed)

CASE

Operands: bits[31:25]=opC, [23:16]=bit_mask, [12:8] =

10 shift

Operation: PC<-PC+((opC&bit_mask)>>shift)+1

BTJ -- Bit test and jump

Operands: bits [31:25] = opC, [24:13] = addr, [12:8] =
bit, [7] = v

15 Operation: if (opC[bit]==v) then PC<-addr

ADDENDUM 8 SEARCH MACHINE

The search machine uses the well-known PATRICIA tree structure (see U.S. Patent 5,546,390 "Method and Apparatus for Radix Decision Packet Processing" issued August 13, 1996 to G.C. Stone and incorporated herein by reference).

Fig. 19 Illustrates tree nodes 2400. Each node is four 64-bit words long. The node formats are as follows.

Search Node format

Abbrev	Name	Size	Description
LCP	Left Child Pointer	16	Pointer to another radix node entry
RCP	Right Child Pointer	16	Pointer to another radix node entry
NAP	Ntwk Addr Pointer	6	Pointer to a network address node
BIX	Bit Index	6	the bit that this radix node is testing for
FLG	Flags	1	bit 54-LVD-Left network address valid in network address node. 0-Invalid; 1-Valid
		1	bit 55-RVD-Right network address valid in network address node. 0-Invalid; 1-Valid
		1	bit 56-LUP-Left Child pointer is an upward pointer or a downward pointer 0-downward; 1-upward
		1	bit 57-RUP-Right Child pointer is an upward pointer or a downward pointer 0-downward; 1-upward
TYP	Type	6	bits 61:58-Tells the type of radix node 0000-Free List Entry. 0001-Static Entry that does not allow for aging. 0010-Learned Entry that allows for aging 0011-Root Entry 0100-Synthetic Entry contains no real key. 0101-Network Entry

			0110-Dirty Entry that is waiting for configuration 0111-User Defined Entry 1000-Aged Entry 1001-Deleted Root entry bits 62 Identifies the timer 0-Timer 0; DEFAULT VALUE 1-Timer 1 63-RESERVED
KEY	Key	48	Different searches compare different number of bits. DA (Ethernet destination address) is 48 bits, IP is 32 bits, SA (Ethernet source address) is 48 bits.
RTP	Root Pointer	16	Pointer to the root of my tree
TSTNP	Timestamp	16	Last time the entry was used
ECNT	Entry Count	16	# of times the entry was used
UNIFO	User Information	64	User definable fields. Ex: UNIFO[63:60] - State. UNIFO[59:56] - Flags. UNIFO[23:0] -VPI/VCI. For Ingress.
NRP	Next Result Pointer	16	Pointer to an optional 4 word entry that is part of the result of this node. 0x00 - means NULL and no additional link exists
NTP	Next Tree Pointer	16	Pointer to a Patricia Tree. Allows hierarchical searching. 0x00 - means NULL and no additional link exists.

Root Node format

Abbrev	Name	Size	Description
LCP	Left Chil Pointer	16	Pointer to another radix node entry
RCP	Right Child Pointer	16	Pointer to another radix node entry
NAP	Ntwk Addr Pointer	16	Pointer to a network address node
BIX	Bit Index	6	the bit that this radix node is testing for. For a ROOT node BIX=0x2f
FLG	Flags	1	bit 54-LVD-Left network address valid in network address node. 0-Invalid; 1-Valid

Abbrev	Name	Size	Description
		1	bit 55-RVD-Right network address valid in network address node. 0-Invalid; 1-Valid
		1	bit 56-LUP-Left Child pointer is an upward pointer or a down-ward pointer 0-downward; 1-upward
		1	bit 57-RUP-Right Child pointer is an upward pointer or a downward pointer 0-downward; 1-upward
TYP	Type	6	bits 61:58-Tells the type of radix node TYPE field is set to 0011 for a ROOT node. Key is implicit in this case; left children see a Key of 0x000000 and right children see a key of 0xffffffff. bit 62-0 bit 63-(RESERVED).
NTP	Next Tree Pointer	16	Next Tree Pointer field is used to link up several roots during the delete tree process. This field is different from the Radix Note NTP field because the SM 190 is the one that gets to write to it. The microcontroller does not have access to this field in a ROOT node. It is used for the sole purpose of deleting trees.

Synthetic Node format

Abbrev	Name	Size	Description
LCP	Left Chil Pointer	16	Pointer to another radix node entry
RCP	Right Child Pointer	16	Pointer to another radix node entry
NAP	Ntwk Addr Pointer	16	Pointer to a network address node
BIX	Bit Index	6	the bit that this radix node is testing for. For a ROOT node BIX=0x2f
FLG	Flags	1	bit 54-LVD-Left network address valid in network address node. 0-Invalid; 1-Valid

Abbrev	Name	Size	Description
		1	bit 55-RVD-Right network address valid in network address node. 0-Invalid; 1-Valid
		1	bit 56-LUP-Left Child pointer is an upward pointer or a downward pointer 0-downward; 1-upward
		1	bit 57-RUP-Right Child pointer is an upward pointer or a downward pointer 0-downward; 1-upward
TYP	Type	6	bits 61:58-Tells the type of radix node TYPE field is set to 0100 for a synthetic entry. Key is derived from the Network Address that is sitting on this synthetic entry. bit 62-0 bit 63-0 (RESERVED).
KEY	Key	48	The key is derived from the network address node that it is storing.
RTP	Root Pointer	16	Pointer to the root of my tree

Network Address Node format

Abbrev	Name	Size	Description
LNA	Left Network Address	32	Network Address
NLRP	Next Left Result Pointer	16	Pointer to a 4 word node where additional results are stored.
LMASK	Left Network Mask	6	Network Mask. Assumes a contiguous mask of 1's. This value tells the position of the last 1
TYPE	Type	6	bits 61:58- 0101 bit 62-0 bit 63-0 (RESERVED)
LUINFO	Left User Information	64	User defined field for the left network address. E.g.: VPI/VCI, State, Flags etc.
RNA	Right Network Address	32	Network Address

Abbrev	Name	Size	Description
RMASK	Right Network Mask	6	Network Mask. Assumes a contiguous mask of 1's. This value tells the position of the last 1
NRRP	Right Next Result Pointer	16	Pointer to a 4 word node where additional results are stored.
RUINFO	Right User Information	64	User defined field for the right network address. E.g. VPI/VCI, State, Flags etc.

Free Node format

Abbrev	Name	Size	Description
TYP	Type	6	bits 61:58- 0000 bit 62-0 bit 63-0 (RESERVED)
NFP	Next Free Pointer	16	Pointer to the next item on the free list

Search Machine commands

A. Search

Abbrev	Name	Size	Description
OP	Op Code	8	bits 3:0=0000 bit 4-Key Length 0-32 bits; 1-48 bits bits 7:5 - (RESERVED)
FLAGS	Flags	8	bit 8 - Auto Learn bit 9 - Auto increment ECNT bits 15:10 - reserved
KEY	Search Key	48	If search is for 32 bit entry, the most significant part is used.
RTP	Root Pointer	16	Pointer to the root of Patricia Tree

- 5 Note: Searching with Root pointer equal NULL will create a new tree.

Host address response

Abbrev	Name	Size	Description
UINFO	User Info	64	The UINFO field of found entry. If not found, the UINFO will be zero.
NTP	Next Tree Pointer	16	Pointer to a next level Patricia tree for hierarchical searching.
RXP	search Node pointer	16	Pointer to the search node that matched the key.
NRP	Next Result Pointer	16	Pointer to an additional 4 word entry
ECNT	Entry Count	16	# of times the entry was used

Network address response

Abbrev	Name	Size	Description
UINFO	User Info	64	The UINFO field of found entry. If not found, the UINFO will be zero.
NAP	Next Tree Pointer	16	Pointer to the network address node that matched.
NRP	Next Result Pointer	16	Pointer to an additional 4 word entry
LRF	Left/Right Ntwrk Addr	1	0-Left Network Address; 1-Right Network Address

B. Insert Host

Abbrev	Name	Size	Description
OP	Op Code	8	bits 3:0 = 0001 bit 4-Key Length 0-32 bits; 1-48 bits bits 7:5-000 (RESERVED).
KEY	Search Key	48	If search is for 32 bit entry, the most significant part is used.
RTP	Root Pointer	16	Pointer to the root of Patricia Tree
RXP	Search Node pointer	16	Pointer to a pre-established Search Node

- 5 Note: If Root pointer equals NULL, new tree will be created.

Response

Abbrev	Name	Size	Description
RTP	Root Pointer	16	Pointer to the root of Patricia Tree
RXP	Search Node pointer	16	Pointer to a pre-established Search Node

C. Insert Network Address

Abbrev	Name	Size	Description
OP	Op Code	8	bits 3:0 = 0010 bit 4-Key Length 0-32 bits; 1-48 bits bits 7:5-000 (RESERVED).
FLAGS	Flags	8	bits 13:8-Mask Level (16 to 47) bits 15:14-reserved
KEY	Search Key	48	Search Key.
RTP	Root Pointer	16	Pointer to the root of Patricia Tree

Response

Abbrev	Name	Size	Description
RTP	Root Pointer	16	Pointer to the root of Patricia Tree
NAP	Next Tree Pointer	16	Network address node where NTWK address was installed
LRF	Left/Right Ntwrk Addr	1	0-Left Network Address; 1-Right Network Address

D. Delete Host

Abbrev	Name	Size	Description
OP	Op Code	8	bits 3:0 = 0011 bit 4-Key Length 0-32 bits; 1-48 bits bits 7:5-000 (RESERVED).
KEY	Search Key	48	Search Key.
RTP	Root Pointer	16	Pointer to the root of Patricia Tree

Response

Abbrev	Name	Size	Description
RTP	Root Pointer	16	Pointer to the root of Patricia Tree
RXP	Search Node pointer	16	Pointer to a Search Node

5

E. Delete Network

Abbrev	Name	Size	Description
OP	Op Code	8	bits 3:0 = 0100 bit 4-Key Length 0-32 bits; 1-48 bits bits 7:5-000 (RESERVED).
FLAGS	Flags	8	bits 13:8-Mask Level (16 to 48) bits 15:14-reserved
KEY	Search Key	48	Search Key.
RTP	Root Pointer	16	Pointer to the root of Patricia Tree

Response

Abbrev	Name	Size	Description
RTP	Root Pointer	16	Pointer to the root of Patricia Tree
NAP	Next Tree Pointer	16	Network address node where NTWK address was installed

Abbrev	Name	Size	Description
RTP	Root Pointer	16	Pointer to the root of Patricia Tree
LRF	Left/Right Ntwrk Addr	1	0-Left Network Address; 1-Right Network Address

F. Delete Tree

Abbrev	Name	Size	Description
OP	Op Code	8	bits 3:0 = 0101 bits 7:4-0000 (RESERVED).
RTP	Root Pointer	16	Pointer to the root of Patricia Tree

Response

Abbrev	Name	Size	Description
RTP	Root Pointer	16	Pointer to the root of Patricia Tree

5 G. Find Network

Abbrev	Name	Size	Description
OP	Op Code	8	bits 3:0 = 0110 bit 4-Key Length 0-32 bits; 1-48 bits bits 7:5-000 (RESERVED).
FLAGS	Flags	8	bits 13:8-Mask Level (16 to 47) bits 15:14-reserved
KEY	Search Key	48	Search Key.
RTP	Root Pointer	16	Pointer to the root of Patricia Tree

Response

Abbrev	Name	Size	Description
RTP	Root Pointer	16	Pointer to the root of Patricia Tree
NAP	Next Tree Pointer	16	Network address node where NTWK address was installed
LRF	Left/Right Ntwrk Addr	1	0-Left Network Address; 1-Right Network Address